

	Type	SPC 4320.320	SPC 5330.320	SPC 5350.320	SPC 6330.320	SPC 6350.320
Panel details	Supported Zones max.	32	128	128	512	512
	Zones on PCB	8	8	16	8	16
	Supported Outputs max.	30	128	128	512	512
	Outputs on PCB	6	6	12	6	12
	Areas	4	16	16	60	60
	Calendars	4	32	32	64	64
	Triggers	8	256	256	1024	1024
	Mapping Gates	4	128	128	512	512
	Virtual Zones	4	20	20	100	100
	Log Intrusion	1.000	10.000	10.000	10.000	10.000
	Log Access	1.000	10.000	10.000	10.000	10.000
	Panel PSU available output	750 mA	750 mA	2.2 A	750 mA	2.2A
	Supported Active languages / System	EN + 4	EN + 4	EN + 4	EN + 4	EN + 4
	Supported battery capacity	7Ah	17Ah	2 x 27Ah	17Ah	2 x 27Ah
	Metal Housing size BxHxT mm	G2	G3	G5	G3	G5
User details	Users	100	500	500	2500	2500
	Paces	32	250	250	250	250
	Access Cards	100	500	500	2500	2500
	SMS	32	50	50	100	100
	Web passwords	32	50	50	100	100
	User Profiles	100	100	100	100	100
	Connectivity	RS232	1	2	2	2
USB		1	1	1	1	1
Ethernet		1	1	1	1	1
Fast Programmer		1	1	1	1	1
X-Bus	X-Bus interface	1	2	2	2	2
	X-Bus devices max.	11	48	48	128	128
	X-Bus keypads	4	16	16	32	32
	X-Bus I/O devices	5	16	16	64	64
	X-Bus output devices	5	16	16	64	64
	X-Bus door expanders	2	8	8	32	32
Access Control	Doors only Entry	4	16	16	64	64
	Doors Entry / Exit	2	8	8	32	32
	Card readers max.	4	16	16	64	64
Transmission	IP dialer EDP / FlexC	on board	on board	on board	on board	on board
	Internal modems max.	2	2	2	2	2
	PSTN modems max.	1 + 1	1 + 1	1 + 1	1 + 1	1 + 1
	GSM modems max. (2G/3G or 2G/4G support)	1 + 1	1 + 1	1 + 1	1 + 1	1 + 1
	FlexC max. no. of supported ATS / ATP	3 / 8	5 / 15	5 / 15	10 / 30	10 / 30
SiWay Wireless	Wireless gateways	5+KP+P	16+KP+P	16+KP+P	64+KP+P	64+KP+P
	Wireless detectors max.	32	120	120	120	120
	FOBs max.	32	50	50	100	100
2-Way Wireless	Emergency buttons max. (WirelessPersonalAlarm)	32	128	128	128	128
	Wireless gateways	1	1	1	1	1
	Wireless keypads	8	8	8	8	8
	Wireless repeaters	4	4	4	4	4
	Wireless detectors max.	32	64	64	64	64
	Wireless output devices max. bells/strobes (int./ext.)	16	16	16	16	16
	Wireless tags max.	32	32	32	32	32
Alarm verification	FOBs max. Transceiver FW < 4.6	32	50	50	64	64
	FOBs max. Transceiver FW >= 4.7	20	20	20	20	20
	Verification zones	4	16	16	32	32
	IP cameras	4	4	4	4	4
	X-BUS Audio expanders max. SPC340 / SPC341 / SPCV440	4	16	16	32	32
E-Bus integration FW 3.6.6	Audio Satellites max. 3 per X-BUS Audio expander	12	48	48	96	96
	E-Bus Gateway	5	5	5	5	5
	Max no. of E-Bus SMT/SAT12/24 (recognized as 8 IN/2OUT)	4	15	14	63	62
	E-BUS SMT /SATdevices zones	16 (4xSxT12)	60 (15xSAT12)	56 (14xSxT12)	252 (63xSxT12)	248 (62xSxT12)
	Max no. of E-Bus PDM-E (recognized as 8 IN/2OUT)	4	15	14	56	56
	E-Bus PDM-E detectors zones	8 (PDM-E)	30 (PDM-E)	30 (PDM-E)	112 (PDM-E)	112 (PDM-E)
	E-Bus Keypads (**1)	4	16	16	16	16
	E-Bus PSUs (**2)	5	16	16	16	16
E-Bus integration FW 3.7.1 and higher	E-Bus SMT44 (recognized as SPCE452)	4	4	4	4	4
	E-Bus Gateway	5	5	5	5	5
	Max no. of E-Bus SMT/SAT12/24 (recognized as 8 IN/2OUT)	4	15	14	63	62
	E-BUS SMT /SATdevices zones	16 (4xSxT12)	60 (15xSAT12)	56 (14xSxT12)	252 (63xSxT12)	248 (62xSxT12)
	Max no. of E-Bus PDM-E (recognized as 2 IN/2OUT)	16	56	56	56	56
	E-Bus PDM-E detectors zones	32 (PDM-E)	112 (PDM-E)	112 (PDM-E)	112 (PDM-E)	112 (PDM-E)
	E-Bus Keypads (**1)	4	16	16	16	16
	E-Bus PSUs (**2)	5	16	16	16	16
E-Bus SMT44 (recognized as SPCE452)	4	4	4	4	4	

Supported E-Bus keypads
 (**1) SAK41/SAK51

Simulation of E-Bus devices