

## DS-PM501Z8T4 Bus Input Expander



- 8 on-board wired zones
- 4 zones programmable as PGM outputs
- Support NEOL/SEOL/DEOL/TEOL/Double Zone/Inertia connection
- Support zone alarm, tamper, masking, fault, short detection
- 1 power output for wired detectors
- 2 Speed-X bus, supporting bus extend distance

*\*DS-PM501Z8T4 is a wired zone expander for AX Hybrid Pro control panel, which has 8 on-board zones and 4 zones is able to configured as PGM outputs. One device can extend the bus distance by 500m. In this way, wired input expander is suitable for small to medium applications, like villa, shop, office, hotel, etc.*

## ▪ Specification

Hardware features	
Tamper-Proof	Front and Rear
Bus	1 input for control panel connection and 1 output for bus extender
Alarm input	8 detectors alarm input
Alarm output	4 PGM output (configurable)
Electrical characteristics	
Power supply	9-16VDC, provided by bus
Power consumption	150 mA @12VDC (Maximum Current) 80 mA @12VDC (Quiescent Current)
Output current	AUX output up to 500mA PGM output up to 200mA
Output voltage	9-16VDC
General	
Dimension (W×H×D)	110 × 155 × 31 mm
Shell material	plastic
Color	white
Weight	225 g
Operation temperature	-20°C to 60°C (-4°F to 140°F)
Operation humidity	10% ~ 90% noncondensing

## ▪ Available Model

DS-PM501Z8T4

**Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
www.hikvision.com



Follow us on social media to get the latest product and solution information.

